

G-7SET - Speaker Set



Pair of professional dual-band transceivers, case set, consisting of 2 transceivers with belt clip, 2 clip-on mics with earphones, charger for 2 transceivers, 2 rech. battery packs.

- 8 PMR channels 446 MHz
- 69 LPD channels 433 MHz
- Boost function for a wide operating range
- High-performance rech. batteries for high operational availability
- Manual transmit mode (PTT) or hands-free voice-activated transmit mode (VOX)
- Monitoring function
- Automatic squelch
- Channel scan mode (SCAN)
- CTCSS tones
- Dual watch
- Vibracall function
- Key lock
- Backlit LCD
- Supplied in a robust hard-sided case

Licence-free, please refer to instruction manual on the MONACOR website.

Tekniset tiedot:

General information

	: -
Description	: hand-held transceiver set
Carrier frequency range	: 446.00625-446.09375 MHz (PMR) 433.075-434.775 MHz (LPD)
Audio frequency range	: -
Channels	: 8 PMR, 69 LPD
THD	: -
Dynamic range	: -
RF S/N ratio	: -
Operating time	: -
Admiss. ambient temp.	: -20 °C to +55 °C
Power supply	: 4 x rech. battery AA size, 800 mAh
Dimensions	: 58 x 195 x 34 mm
Total weight	: 1.203 kg
Connections	: 2.5 mm jack (microphone) 3.5 mm jack (speaker)

Specifications transmitter

	: -
Transmitting power	: 500 mW
Operating range	: ? 5,000 m
Power supply transmitter	: -
Width transmitter	: -
Height transmitter	: -
Depth transmitter	: -
Weight transmitter	: -
Connections transmitter	: -
Specifications receiver	: -
Audio signal receiver	: -
Power supply receiver	: -
Width receiver	: -
Height receiver	: -
Depth receiver	: -
Weight receiver	: -
Connections receiver	: -