

ULM-164/SW - Line Mixer



Universal line mixer,
6 channels.

- 6 stereo inputs/mono inputs
- 2 stereo outputs, independent of each other (master 1 via RCA and 6.3 mm jack), 1 mono output
- 3-way equalizer
- LED VU meter, switchable for both outputs
- Clip LED for each channel
- Balance controls with centre click for the stereo input channels
- Extended muting function
- Adjustable headphone output
- 482 mm (19") rack installation, 1 RS

Tekniset tiedot:

| | |
|--------------------|---|
| No. of channels | : 6 |
| No. of inputs | : 12 |
| Mic input | : - |
| Line input | : 150 mV/50 kOhm (stereo), 6 x RCA L/R 150 mV/25 kOhm (mono), 6 x 6.3 mm jack, unbal. |
| CD input | : - |
| Phono input | : - |
| Tape (play) | : - |
| Aux input | : - |
| Insert input | : - |
| Effect return | : - |
| Master output | : 1 V/600 Ohm (stereo), 2 x RCA (1 x 6.3 mm) L/R 2 V/600 Ohm (mono), 1 x 6.3 mm jack |
| Record output | : - |
| Monitor output | : - |
| Booth output | : - |
| Aux output | : - |
| Insert output | : - |
| Effect send | : - |
| Control room | : - |
| Tape (rec) | : - |
| Headphones | : ? 8 Ohm, 1 x 6.3 mm jack |
| Gooseneck lamp | : - |
| WiFi | : - |
| USB | : - |
| Bluetooth | : - |
| Frequency range | : 20-20,000 Hz |
| THD | : 0.05% |
| S/N ratio | : 69 dB, unweighted |
| Crosstalk | : - |
| Equalizer bass | : ± 12 dB/80 Hz |
| Equalizer midrange | : ± 12 dB/1 kHz |
| Equalizer treble | : ± 12 dB/10 kHz |
| equalizer | : - |
| Talkover | : - |
| Phantom power | : - |
| Crossfader | : - |

| | |
|--|------------------------------|
| Media player | : - |
| Amplifier | : - |
| Power supply | : ∿ 230Â V/50Â Hz/10Â VA |
| Mains voltage | : ∼ 230 V |
| Mains frequency | : 50 Hz |
| Power consumption, operation | : 10 VA |
| Operating voltage (possible alternative) | : - |
| Power supply (possible alternative) | : - |
| Admiss. ambient temp. | : 0-40 °C |
| Width | : 482 mm |
| Height | : 48 mm |
| Depth | : 175 mm |
| Rack spaces, RS | : 1 |
| Weight | : 2.3 kg |