

FGA-22HQ - Cable Adaptor



High-end transformer,
for connecting speaker outputs of a car radio to the line inputs of an amplifier.

- Internal ground separation
- Adjustable output level
- Screw terminals, gold-plated RCA jacks
- Max. input power: 20 W
- Input/output impedance: 45 Ohm/30 Ohm-2.8 kOhm
- Frequency range: 20-30,000 Hz
- THD: < 0.001%
- 42 x 29 x 96 mm, 104 g

Tekniset tiedot:

| | |
|-----------------------|--------------------|
| Description | : transformer |
| Frequency range | : 20-30,000 Hz |
| Control range | : - |
| Control frequencies | : - |
| Input signal | : - |
| Input sensitivity | : - |
| Input impedance | : 45 Ohm |
| Output signal | : - |
| Output impedance | : 30Ω Ohm-2.8 kOhm |
| Gain | : - |
| Phantom power | : - |
| Compression | : - |
| Gate ratio | : - |
| Crossover frequency | : - |
| High-pass filter | : - |
| Low cut | : - |
| Transmission ratio | : - |
| S/N ratio | : - |
| Channel separation | : - |
| THD | : < 0.001% |
| Admiss. ambient temp. | : 0-40 °C |
| Power supply | : - |
| Dimensions | : 42 x 29 x 96 mm |
| Weight | : 104 g |
| Inputs | : screw terminals |
| Outputs | : 1 x RCA L/R |
| Other features | : - |