

## FGA-22S - REM generator



Transformer with switching voltage generation,  
for car radios only, for connecting speaker outputs of a car radio to the line inputs of an amplifier.

- For operation with car audio systems which do not feature a switching voltage output
- Switching voltage (REM) is generated independently of the audio signal, even when the music stops
- Internal ground separation
- Screw terminals, gold-plated RCA jacks
- Max. input power: 20 W
- Input/output impedance: 20 kOhm/10 kOhm
- Frequency range: 20-30,000 Hz
- THD: < 0.01%
- Power supply: DC 12 V/25 mA
- 43 x 27 x 100 mm, 70 g

## Tekniset tiedot:

|                       |                    |
|-----------------------|--------------------|
| Description           | : transformer      |
| Frequency range       | : 20-30,000 Hz     |
| Control range         | : -                |
| Control frequencies   | : -                |
| Input signal          | : -                |
| Input sensitivity     | : -                |
| Input impedance       | : 20 kOhm          |
| Output signal         | : -                |
| Output impedance      | : 10 kOhm          |
| Gain                  | : -                |
| Phantom power         | : -                |
| Compression           | : -                |
| Gate ratio            | : -                |
| Crossover frequency   | : -                |
| High-pass filter      | : -                |
| Low cut               | : -                |
| Transmission ratio    | : -                |
| S/N ratio             | : -                |
| Channel separation    | : -                |
| THD                   | : < 0.01%          |
| Admiss. ambient temp. | : 0-40 °C          |
| Power supply          | : DC 12V/25 mA     |
| Dimensions            | : 43 x 27 x 100 mm |
| Weight                | : 60 g             |
| Inputs                | : screw terminals  |
| Outputs               | : 1 x RCA L/R      |
| Other features        | : -                |