

MA-100/15 - Mike Matching Transformer



Microphone matching transformer, with Hi/Lo switch. With balanced XLR connection as well as 6.3 mm plug, unbalanced, with 15 cm microphone cable.

- Frequency range: 50-15,000 Hz
- Input impedance: 600 Ohm
- Transformation ratio: 1:10/1:1 (1 kHz)

Tekniset tiedot:

Description	: Microphone matching transformer
Nominal value	: 50-15,000 Hz, 600 Ohm
Type	: with Hi/Lo switch
Colour	: chrome/black
Material	: -
Suitable for	: -
Power supply	: -
Admiss. ambient temp.	: 0-40 °C
Dimensions	: -
Length	: -
Mounting dimensions	: -
Weight	: 80 g
Connections	: 1 x XLR, bal. 1 x 6.3 mm plug, unbal.
Other features	: transformation ratio: 1:10/1:1 (1Â kHz)
Packing unit	: 1