

TXA-800HSE - Microphone Transmitter



Multifrequency pocket transmitter, with UHF PLL technology. Matching portable amplifier systems of the TXA-1000 series, TXA-800 series and TXA-800R.

- 1 headband microphone (omnidir. char.), 1 tie clip microphone (cardioid char.)
- 16 selectable UHF frequencies (863.1-864.9 MHz)
- Metal housing
- Microphone connection via 3-pole mini XLR jack
- Audio line input via 3.5 mm stereo jack
- Sensitivity to be adjusted in 3 steps
- Mute function
- Backlit LCD for indicating channel/frequency and battery status
- Transmitting power: 10 mW (EIRP)
- Power supply via 2 x 1.5 V battery AA size (not supplied)
- Belt clip

Licence-free in the EU.

tastenwelt 02/2008

“The use of the headset is interesting for keyboard players.”

Tekniset tiedot:

General information

	: -
Description	: pocket transmitter
Carrier frequency range	: 863.1-864.9 MHz
Audio frequency range	: 70-16,000 Hz
Channels	: 1
THD	: -
Dynamic range	: -
RF S/N ratio	: -
Operating time	: -
Admiss. ambient temp.	: 0-40 °C
Power supply	: -
Dimensions	: -
Total weight	: -
Connections	: -

Specifications transmitter

	: -
Transmitting power	: 10 mW
Operating range	: 30 m
Power supply transmitter	: 2 x 1.5 V batt. AA size
Width transmitter	: 65 mm
Height transmitter	: 95 mm
Depth transmitter	: 30 mm
Weight transmitter	: 110 g
Connections transmitter	: 1 x 3-pole mini XLR
Specifications receiver	: -
Audio signal receiver	: -
Power supply receiver	: -
Width receiver	: -
Height receiver	: -
Depth receiver	: -
Weight receiver	: -
Connections receiver	: -