

## MMX-30 - Line Mixer



Compact 3-channel stereo line mixer

- 3 stereo input channels with one level control each
- 1 stereo master output, adjustable
- RCA connections for input channels and output
- 2 stereo headphone outputs, common control
- Signal/peak LEDs for the input channels and peak LED for the output

## Tekniset tiedot:

No. of channels	: -
No. of inputs	: -
Mic input	: -
Line input	: 40Â mV, 3 x RCA L/R
CD input	: -
Phono input	: -
Tape (play)	: -
Aux input	: -
Insert input	: -
Effect return	: -
Master output	: 4Â V, 1 x RCA L/R
Record output	: -
Monitor output	: -
Booth output	: -
Aux output	: -
Insert output	: -
Effect send	: -
Control room	: -
Tape (rec)	: -
Headphones	: 2 x 10 mW/2 x 32Â Ohm, 2 x 6.3 mm jack
Gooseneck lamp	: -
WiFi	: -
USB	: -
<b>Bluetooth</b>	: -
Frequency range	: 5-30,000 Hz
THD	: < 0.1%
S/N ratio	: ? 66 dB
Crosstalk	: -
Equalizer bass	: -
Equalizer midrange	: -
Equalizer treble	: -
equalizer	: -
Talkover	: -
Phantom power	: -
Crossfader	: -

Media player	: -
Amplifier	: -
Power supply	: via encl. plug-in power supply
Mains voltage	: -
Mains frequency	: -
Power consumption, operation	: -
Operating voltage (possible alternative)	: -
Power supply (possible alternative)	: -
Admiss. ambient temp.	: 0-40 °C
Width	: 147 mm
Height	: 50 mm
Depth	: 119 mm
Rack spaces, RS	: -
Weight	: 693 g